

| 型号: JGA25-370 | | | | 参数表 | | | | | | | | | |
|---------------|--------|-----------|---------|---------------|---------|--------|--------|---------|---------|------------|------|--------|--|
| 电压Voltage | | 空载No Load | | 负载Load Torque | | | | 堵转Stall | | 减速器Reducer | | 重量 | |
| 范围 | 额定 | 转速 | 电流 | 转速 | 电流 | 扭矩 | 功率 | 扭矩 | 电流 | 减速比 | 尺寸 | Weight | |
| Workable | Rated | Speed | Current | Speed | Current | Torque | Output | Torque | Current | Ratio | Size | 单位 | |
| Range | Volt.V | rpm | ma | rpm | ma | kg.cm | W | kg.cm | ma | 01:00 | mm | 约g | |
| 3-9V | 6V | 1363 | 80 | 1090 | 380 | 0.1 | 2 | 0.8 | 900 | 4.4 | 18 | 80 | |
| 3-9V | 6V | 646 | 80 | 516 | 380 | 0.23 | 2 | 1.5 | 900 | 9.6 | 17.5 | 82 | |
| 3-9V | 6V | 281 | 80 | 238 | 380 | 0.5 | 2 | 4 | 900 | 21 | 19 | 84 | |
| 3-9V | 6V | 176 | 80 | 150 | 380 | 0.85 | 2 | 5 | 900 | 35 | 21 | 85 | |
| 3-9V | 6V | 133 | 80 | 113 | 380 | 1.1 | 2 | 6 | 900 | 45 | 21 | 86 | |
| 3-9V | 6V | 77 | 80 | 65 | 380 | 1.95 | 2 | 10 | 900 | 78 | 23 | 88 | |
| 3-9V | 6V | 58 | 80 | 46 | 380 | 3 | 2 | 15 | 900 | 103 | 23 | 89 | |
| 3-9V | 6V | 35 | 80 | 28 | 380 | 4 | 2 | 25 | 900 | 171 | 25 | 91 | |
| 3-9V | 6V | 26 | 80 | 20 | 380 | 5 | 2 | 35 | 900 | 226 | 25 | 92 | |
| 3-9V | 6V | 16 | 80 | 13 | 380 | 9 | 2 | 禁止 | 900 | 377 | 27 | 94 | |
| 3-9V | 6V | 12 | 80 | 10 | 380 | 10 | 2 | 禁止 | 900 | 500 | 27 | 96 | |
| 6-18V | 12V | 1931 | 50 | 1351 | 250 | 0.11 | 4 | 0.44 | 1200 | 4.4 | 18 | 80 | |
| 6-18V | 12V | 915 | 50 | 640 | 250 | 0.24 | 4 | 1 | 1200 | 9.6 | 17.5 | 82 | |
| 6-18V | 12V | 399 | 50 | 279 | 250 | 0.55 | 4 | 2.2 | 1200 | 21 | 19 | 84 | |
| 6-18V | 12V | 250 | 50 | 175 | 240 | 0.95 | 4 | 38 | 1200 | 35 | 21 | 85 | |
| 6-18V | 12V | 188 | 50 | 131 | 240 | 1.26 | 4 | 5 | 1200 | 45 | 21 | 86 | |
| 6-18V | 12V | 108 | 50 | 75 | 240 | 2.1 | 4 | 8.4 | 1200 | 78 | 23 | 88 | |
| 6-18V | 12V | 82 | 50 | 57 | 240 | 2.88 | 4 | 11 | 1200 | 103 | 23 | 89 | |
| 6-18V | 12V | 50 | 50 | 40 | 240 | 4.78 | 4 | 18 | 1200 | 171 | 25 | 91 | |
| 6-18V | 12V | 37 | 50 | 29 | 240 | 6.3 | 4 | 14 | 1200 | 226 | 25 | 92 | |
| 6-18V | 12V | 22 | 50 | 17 | 240 | 10 | 4 | 禁止 | 1200 | 377 | 27 | 94 | |
| 6-18V | 12V | 17 | 50 | 13 | 240 | 14 | 4 | 禁止 | 1200 | 500 | 27 | 96 | |
| 12-36V | 24V | 863 | 10 | 604 | 70 | 0.083 | 1 | 0.4 | 220 | 4.4 | 18 | 80 | |
| 12-36V | 24V | 409 | 10 | 280 | 70 | 0.17 | 1 | 0.88 | 220 | 9.6 | 17.5 | 82 | |
| 12-36V | 24V | 178 | 10 | 125 | 70 | 0.4 | 1 | 2 | 220 | 21 | 19 | 84 | |
| 12-36V | 24V | 111 | 10 | 80 | 70 | 0.64 | 1 | 3.2 | 220 | 35 | 21 | 85 | |
| 12-36V | 24V | 84 | 10 | 60 | 70 | 0.85 | 1 | 4.2 | 220 | 45 | 21 | 86 | |
| 12-36V | 24V | 48 | 10 | 35 | 70 | 1.4 | 1 | 7.4 | 220 | 78 | 23 | 88 | |
| 12-36V | 24V | 36 | 10 | 25 | 70 | 1.9 | 1 | 9.5 | 220 | 103 | 23 | 89 | |
| 12-36V | 24V | 22 | 10 | 15 | 70 | 3.2 | 1 | 16 | 220 | 171 | 25 | 91 | |
| 12-36V | 24V | 17 | 10 | 12 | 70 | 4.2 | 1 | 21 | 220 | 226 | 25 | 92 | |
| 12-36V | 24V | 10 | 10 | 7 | 70 | 7 | 1 | 35 | 220 | 377 | 27 | 94 | |
| 12-36V | 24V | 7.5 | 10 | 5 | 70 | 9.5 | 1 | 47 | 220 | 500 | 27 | 96 | |